

BORK Error Code (U802 / U803)

Cause	Status Explanation	Key Movement	Display
1. No inner Pot	IH Power put into the cooker without inner pot	<ul style="list-style-type: none"> - Impossible to put the button (except cancel button) - Every heater is shorted. 	
2. Top Sensor Open	Mark when the Top Sensor open Sensor hex is more "0xFD" (under -16°C)	<ul style="list-style-type: none"> - Impossible to put the button - Every heater is shorted - Turn to the normal mode when the sensor connected normally - The normal range for Sensor hex 0x3 < Sensor Hex < 0xFD 	Err 2
3. Top Sensor Short (Same as Top Sensor high heating)	When Top Sensor is short or over-heating Sensor hex is under "0x3"(over200°C)		Err 3
4. Bottom Sensor Open	When the Bottom Sensor is opened Maintain 3 seconds when the Sensor hex is over "0xFD"(-16°C under)	<ul style="list-style-type: none"> - Impossible to put the button - Every heater is shorted - Turn to the normal mode when the sensor connected normally - The normal range for Sensor hex 0x3 < Sensor Hex < 0xFD 	Err 4
5. Bottom Sensor Short (Same as Top Sensor high heating)	When the Bottom Sensor is Short or overheated When Sensor hex in under "0x3"(over 200°C)		W
6. Environment Sensor Open	When the environment sensor is opened, Sensor hex is over "0xE4"(under -20°C)	<ul style="list-style-type: none"> - The environment sensor have problem, the warming algorithm is operating as basic algorithm.(default algorithm) - No error mark directly and mark the environment checking of the DEMO mode - The normal range for Sensor hex 0x16 <= Sensor Hex <=0xFD 	Err 6
7. Environment Sensor Short	When the environment sensor is shorted Sensor hex is under "0x16"(100°C over)		Err 7

BORK Error Code (U802 / U803)

Cause	Status Explanation	Key Movement	Display
8. Bottom Sensor Wrong Movement	<ul style="list-style-type: none">- After cooking start and some procedure is finished, the temperature of B/S is under standard, the bottom sensor recognize as wrong movement. - Power code OFF -> ON operating <input type="checkbox"/> turn to the regular mode	※ Time Protect will be blocking, the error is happened.	Err 8