

Radiation test of LV supply and components in PSI 30.6.2002

- **Requirements:**
 - tid max 32 krad / 10years
 - see $1.75e12$ p/cm²
 - beam has $5e8$ p/cm²/s ~ 7 minutes to reach 30krads
to get $1.75e12$ p/cm² for SEE test and in the same time to limit TID we had to multiply the number of components tested by 8
- **Component test**
 - **Tested MOSFETS for SEE**
 - Primary side of DCDC
 - IRFP460 TO247
 - IRFP9N60 TO263 (SMD)
 - Secondary side of DCDC
 - IRF260 TO247
 - IRF3710 TO263
- **Module test**
 - Original LT converter based on LTC1698 & LT1681
 - Half bridge converter with IRFP460, IR2110 & UC3526
 - Optically isolated amplifier with HCPL7840 & LM6142

Radiation test of LV supply and components in PSI 30.6.2002

- **Component tests**
 - **Test1 - SEE in irfp460 6 samples**
 - 200V Uds , Flux -> $5e8 \text{ p/cm}^2/\text{s}$
40krads -> 9.5 minutes - $2.91e11 \text{ p/cm}^2$
 - result =NOSEE
 - **Test 2 - same as 1 but 250 Vce**
 - result NOSEE
 - **Test3 - SEE in 8x IRF3710**
 - unfortunately 200V on collector for 3 minutes then 50V set then conditions as test1
result NOSEE
 - **Test 4 - Same as 3**
 - Increased voltage to 80 V ,other conditions the same
 - result NOSEE
 - **Test5 - 8x IRFP9N60**
 - 200V Uds
 - result NOSEE
 - **Test6 - same as 5**
 - 250V Uds
 - result number 4 had SEE after ~8minutes
 - rest NOSEE

Radiation test of LV supply and components in PSI 30.6.2002

- **Module test**
 - **Test 7 - LT DCDC converter**
 - 40v input 5v/9A output
 - Up to 17 krads working well
 - 6V output shift ~ 17krads & SEE
 - then continue 19.2krad next SEE
 - then continue up to 28.2krads and there was again SEE
 - then continue up to 38 krads and again SEE
 - then after stop the beam without power cycling function is back
 - **Test8 OIA**
 - two ramps without radiation
 - 20krads
 - ramp
 - 10krads
 - ramp
 - 10krads
 - ramp
 - **Preliminary result is that transfer function is still linear with constant gain up to 40krads**

Radiation test of LV supply and components in PSI 30.6.2002

- **Test9**
DCDC Halfbridge
30krads without on-line
outp.voltage drop to 0 but fuse still OK. Suspicious high-side driver IR2110 ??
- **Test10**
8x IRFP260
result NOSEE